

**Uteffekt från enskild port:**

**USB-C1/C2 PD 3.0 och QC 4+ (stöd för PPS):** 3,3 - 11 V = 5 A, 5,0 V = 3,0 A, 9,0 V = 3,0 A, 12,0 V = 3,0 A, 15,0 V = 3,0 A, 20,0 V = 3,25 A 65,0 W max. vardera.

**USB-A1 QC 3,0:** 4,5 V = 5,0 A, 5,0 V = 4,5 A, 5,0 V = 3,0 A, 9,0 V = 3,0 A, 12,0 V = 3,0 A, 20,0 V = 3,0 A 60,0 W max.

**USB-A2:** 5,0 V = 1,0 A, 5,0 W max.

**Uteffekt från dubbla portar:****USB-C1+C2**

USB-C1: 5,0 V = 3,0 A, 9,0 V = 2,22 A, 12,0 V = 1,67 A 20,0 W max.

USB-C2: 5,0 V = 3,0 A, 9,0 V = 3,0 A, 12,0 V = 3,0 A, 15,0 V = 3,0 A, 20,0 V = 2,25 A 45,0 W max.

**USB-C1+USB-A1**

USB-C1+USB-A1: 5,0 V = 3,0 A, 15,0 W

**USB-C1+USB-A2**

USB-C1: 5,0 V = 3,0 A, 9,0 V = 3,0 A, 15,0 V = 3,0 A, 20,0 V = 3,25 A 65,0 W

USB-A2: 5,0 V = 1,0 A, 5,0 W

**USB-C2+USB-A1**

USB-C2: 5,0 V = 3,0 A, 9,0 V = 3,0 A, 12,0 V = 3,0 A, 15,0 V = 3,0 A, 20,0 V = 2,25 A 45,0 W

USB-A1: 5,0 V = 3,0 A, 9,0 V = 2,0 A, 18,0 W

**USB-C2+USB-A2**

USB-C2: 5,0 V = 3,0 A, 9,0 V = 3,0 A, 15,0 V = 3,0 A, 20,0 V = 3,25 A 65,0 W

USB-A2: 5,0 V = 1,0 A, 5,0 W

**USB-A1+USB-A2**

USB-A1: 5,0 V = 3,0 A, 9,0 V = 3,0 A, 15,0 V = 3,0 A, 20,0 V = 3,0 A 60,0 W

USB-A2: 5,0 V = 1,0 A, 5,0 W

**Uteffekt från kombinerad port:****USB-C1+C2+A1**

USB-C1+USB-A1: 5,0 V = 3,0 A, 15,0 W

USB-C2: 5,0 V = 3,0 A, 9,0 V = 3,0 A, 12,0 V = 3,0 A, 15,0 V = 3,0 A, 20,0 V = 2,25 A 45,0 W

**USB-C1+C2+A2**

USB-C1: 5,0 V = 3,0 A, 9,0 V = 2,22 A, 12,0 V = 1,67 A 20,0 W max.

USB-C2: 5,0 V = 3,0 A, 9,0 V = 3,0 A, 12,0 V = 3,0 A, 15,0 V = 3,0 A, 20,0 V = 2,25 A 45,0 W max.

USB-A2: 5,0 V = 1,0 A, 5,0 W max.

**USB-C1+A1+A2**

USB-C1+A1: 5,0 V = 3,0 A, 15,0 W

USB-A2: 5,0 V = 1,0 A, 5,0 W

**USB-C2+A1+A2**

USB-C2: 5,0 V = 3,0 A, 9,0 V = 3,0 A, 12,0 V = 3,0 A, 15,0 V = 3,0 A, 20,0 V = 2,25 A 45,0 W

USB-A1: 5,0 V = 3,0 A, 9,0 V = 2,0 A, 18,0 W

USB-A2: 5,0 V = 1,0 A, 5,0 W

**USB-C1+CC2A1+A2**

USB-C1+A1: 5,0 V = 3,0 A, 15,0 W max.

USB-C2: 5,0 V = 3,0 A, 9,0 V = 3,0 A, 12,0 V = 3,0 A, 15,0 V = 3,0 A, 20,0 V = 2,25 A 45,0 W max.

USB-A2: 5,0 V = 1,0 A, 5,0 W max.

Total DC-uteffekt: 65,0 W max.